



Tech Tip

Using the UNO-TS2 with ACA-E5 Controller

Firmware Version

For use with the ACA-E5 controller, the UNO-TS2/UNO-TS2D firmware and screens must be updated to the following minimum versions: Screens: 3.01.00 -- Firmware: 1.67. Updated firmware can be found in the Document Center at www.russound.com

UNO-TS2 and KLK-E5 in Same Zone

If more than one keypad and touchscreen is desired for a zone, use an optional SA-ZX3 keypad splitter with a 1201A 1-amp power supply at the controller end. The SA-ZX3 will support 1 UNO-TS2/UNO-TS2D plus up to 2 KLK-E5s. All keypads on an SA-ZX3 control the same zone and need to be assigned the same zone ID. More detailed information regarding SA-ZX3 installation and operation can be found in its installation manual.

UNO-TS2 Setup Procedure

When used with the ACA-E5, the UNO-TS2 automatically assigns the correct screen template to source type. However, the UNO-TS2 **must** be assigned the Zone # and Controller ID (under Installer Setup).

UNO-TS2 Home Screens

To accommodate the number of possible sources (12) connected to the ACA-E5, the UNO-TS2 home screen will show the names of the first five sources and a "More Sources" button to reach the second home screen and the remaining sources.



UNO-TS2 home screen showing button for "More Sources"

Sphere Technical Support: 1-866-604-5245
M - F 8:30 a.m. - 7 p.m. EST



SPHERE™

Premier products for Russound-
SPHERE™ Certified Professionals

The Sphere Certified Integrator Program is a premium service program for experienced multiroom audio and video dealers. For more information on the Sphere program please visit www.russoundsphere.com



5 Forbes Road, Newmarket, New Hampshire 03857 USA

603.659.5170

www.russound.com

©2009 Russound. All rights reserved. All trademarks are the property of their respective owners. Specifications are subject to change without notice. Russound is not responsible for typographical errors or omissions. 03/03/09